

Beskrivelse:	FCO921 Set II	FCO921 Set I
<b>Strømforsyning:</b>	Power supply by Motorola mobile radio MTM5400 230VAC/ 10.8 to 15.6 V/ DC Power supply PC 230VAC/12-19VDC/ 65 W	Power supply by Motorola mobile radio MTM5400 230VAC/ 10.8 to 15.6 V/ DC
<b>Strømforbruk</b>	Min.: 106 mA (one switched output) Max.: 214 mA (four switched outputs) Standby: 70 mA (no switched output)	Min.: 106 mA (one switched output) Max.: 214 mA (four switched outputs) Standby: 70 mA (no switched output)
<b>Inngangseffekt</b>	Min.: 1.64 W (one switched output) Max.: 22,44 W (four switched outputs) Standby: 1,24 W (no switched output)	Min.: 1.24 W (one switched output) Max.: 2,44 W (four switched outputs) Standby: 0,84 W (no switched output)
<b>Temperaturområde</b>	Operation -20 °C to +50 °C temperature range Storage - 40 °C to +70 °C temperature range Avoid incident solar radiation	Operation -20 °C to +50 °C temperature range Storage - 40 °C to +70 °C temperature range Avoid incident solar radiation
<b>Mål i millimeter</b>	approx. 485 x 280 x 90mm (H x W x D) 19" / 2HE	approx. 210 x 130 x 80mm (H x W x D)
<b>Vekt</b>	approx. 7,5 kg	approx. 1 kg
<b>Innkapsling</b>	steel panel (black)	plastic ABS (grey)
<b>IP klasse</b>	IP20	IP54
<b>Montering</b>	Skruer	Skruer
<b>Kontaktkabler</b>	Cable between Motorola MTM5400 and FCO921 // HDMI to Monitor (Display)	KAS077 (FCO921 <-> MTM5400)
<b>Utganger</b>	4 x relay output: max. nominal current 16 A max. contact voltage 250 V/AC	4 x relay output: max. nominal current 16 A max. contact voltage 250 V/AC
<b>Interface</b>	HDMI FCO921 to Monitor (FCO9210 Viewer)	serial interface FCO921 <-> PC (RS232)
<b>Sendernetverk</b>	TETRA	TETRA
<b>Max sendereffekt</b>	max. 10 W (Motorola MTM5400)	max. 10 W (Motorola MTM5400)
<b>Frekvensområde</b>	410-430 MHz 450-470 MHz	410-430 MHz 450-470 MHz